

LM-211IA Integrated tube amplifier – Push Pull EL34 – 2x32W

HIGHLIGHTS

- ✓ Point-to-point wiring
- ✓ Triode/ultra-linear modes
- ✓ High quality components

LOGISTICAL DATA

EAN Code Silver: 0712038177110

DEEE 4.4 = 0,84 € H.T. = 1 € T.T.C.

Dimensions (WxHxD) & Weight

PRODUCT 376 x 192 x 345 mm / 19.6 Kg

PACKAGING 490 x 260 x 400 mm / 22.5 Kg



Line Magnetic Audio is a brand of High end products founded in 2005. Now it has become well known with its series reproduction of music and regarded as a forerunner in presenting innovative products with cutting edge technology and lasting intrinsic value. Tube electronics, CD players, Classic horns, Classis field coil speakers, DACs, a lot of different series of products we are working on not only Classis electronics but also new technology on dacs and CD players.

The Line Magnetic integrated amplifier LM-2111A is a push pull amplifier with 4x EL34 tubes in Class AB amplification and delivers 2x15W in triode mode and 2x32W in ultra-linear mode. It has 4 balanced line inputs and $4/8\Omega$ output groups.

The rear-illuminated front panel meter is used to adjust the polarization of the tubes.

The use of high quality components (Realcap capacitors, ALPS potentiometer) wired in the air for the most part is the guarantee of exemplary reliability. Its transformers output are of EI type, specially disigned for power supply.

The LM-211iA delivers dynamic, rich and natural sound.

TUBES

Input stage: 2x 12AX7 et 2x 12AU7 Power stage: 4x EL34

c. .

Hand-made construction with the finest point-to-point wiring Bias control is accessible on top of the amplifier panel with true ampere meter. Analog Inputs: 4 line inputs Load impedance: $4/8\Omega$ SoftStart and time-delay circuit. (30 seconds) Specially designed EI transformer for power supply Two EI output transformers with wide bandwidth are applied ALPS volume control and Realcap capacitors are applied.

Metal and removable tube guard cage Infrared Remote control

Tubes Basics	Common Replacements
12AX7	12AX7EH, ECC83, E83CC, CV4004, ECC803, 5751
12AU7	ECC82, 12AU7EH, 5814, 6189, CV4003
EL34	6CA7

SPECIFICATIONS

Class AB amplifier 2x15W RMS Triode 2x32W RMS Ultra-linear Tubes: 2x 12AX7, 2x 12AU7, 4x EL34

THD: 1% (1kHz) Signal/Noise ratio: 88dB (Weighted A) Frequency response: 10 to 50.000 Hz (-1.5 dB) Sensitivity: 200 mV (Built-in Mode) Input Impedance: 100kΩ Load impedance for HP to connect: 4/8Ω

Connectors

4x Line Inputs RCA (pair) 2x Screw terminals compatible with banana plugs

Included Accessories

2x Fuses 1x Remote control 1x Detachable power cord 1x Manual

